

# Xitanium LED downlight and spotlight drivers

Dimmable and/or programmable drivers



## Product specification

Product name	Housing	Housing	Dimming range	Output current range	Output voltage range	Central DC operation	SELV	DALI / Touch&Dim & programmable	Trailing edge dim	SimpleSet	Order code
	type	mm	%	A	V						EOC
Xitanium 75W SH 0.3-1A 110V TDI 230V	4	220x83x35	100-1	0.3-1.0	55-110	*	*	*			8718291 728030 00
Xitanium 50W LH 0.3-1A 62V TD/I 230V	2	190x46x32	100-1	0.3-1.0	31-62	*	*	*			8718291 710950 00
Xitanium 50W LH 0.7-1.5A 48V TD/I 230V	2	190x46x32	100-1	0.7-1.5	24-48	*	*	*			8718291 782360 00
Xitanium 50W WH 0.7-1.5A 54V TD/Is 230V	5	200x74x32	100-1	0.7-1.5	24-54	*	*	*		*	8718696 538111 00
Xitanium 36W WH 0.3-1.0A 54V TD/Is 230V	5	200x74x32	100-1	0.3-1.0	24-54	*	*	*		*	8718696 515587 00
Xitanium 36W LH 0.3-1A 48V TD/I 230V	2	190x46x32	100-1	0.3-1.0	24-48	*	*	*			8718291 729037 00
Xitanium 36W/s 0.3-1A 48V TD 230V	3	110x75x31	100-1	0.3-1.0	24-48	*	*	*			8718291 770947 00
Xitanium 36W/m 0.3-1.05A 54V TD 230V	6	97x43x30	100-1	0.3-1.05	24-54	*	*	*			8718696 748725 00
Xitanium 25W LH 0.3-1A 36V TD/Is 230V	1	150x46x32	100-1	0.3-1.0	18-36	*	*	*			8728291 708032 00
Xitanium 20W WH 0.15-0.5A 54V TD/Is 230V	5	200x74x32	100-1	0.15-0.5	24-54	*	*	*		*	8718696 531884 00
Xitanium 20W LH 0.15-0.5A 48V TD/Is 230V	1	150x46x32	100-1	0.15-0.5	24-48	*	*	*			8718291 782346 00
Xitanium 20W/m 0.15-0.5A 54V TD 230V	6	97x43x30	100-1	0.15-0.5	24-54	*	*	*			8718696748749 00

These drivers are compatible with Fortimo LED DLM and SLM modules.

For details on LED module and cable combinations see pages 38-52.

Fixed output



## Product specification

Product name	Housing	Housing	Output current range	Output voltage range	Central DC operation	SELV	SimpleSet	Order code
	type	mm	A	V				EOC
Xitanium 75W SH 0.3-1A 110V I 230V	4	220x83x35	0.3-1	55-110	*	*		8718291 676256 00
Xitanium 50W WH 0.7-1.5A 54V Is 230V	6	200x74x32	0.7-1.5	24-54	*	*	*	8718696 683644 00
Xitanium 50W WH 0.7-1.5A 54V S 230V	3	110x74x32	0.7-1.5	24-54	*	*	*	8718696 683705 00
Xitanium 50W SH 0.3-1A 62V I 230V	4	220x83x35	0.3-1	31-62	*	*		8718291 676218 00
Xitanium 50W LH 0.7-1.5A 48V I 230V	2	190x46x32	0.7-1.5	24-48	*	*	*	8718696 437629 00
Xitanium 50W/s 0.3-1A 62V 230V	3	110x75x32	0.3-1	31-62	*	*		8718291 676157 00
Xitanium 50W/s 0.9-1.4A 48V 230V	3	110x75x32	0.9-1.4	24-48	*	*		8718291 777588 00
Xitanium 50W/m 0.7-1.5A 54V 230V	5	97x43x30	0.7-1.5	24-54	*	*	*	8718696 659090 00
Xitanium 50W/m 0.7-1.5A 48V 230V	5	97x43x30	0.7-1.5	24-48	*	*		8718696 437186 00
Xitanium 43W/m 0.7-1.2A 54V 230V	5	97x43x30	0.7-1.2	24-54	*	*	*	8718696 659076 00
Xitanium 36W WH 0.3-1.05A 54V Is 230V	6	200x74x32	0.3-1.05	24-54	*	*	*	8718696 683620 00
Xitanium 36W WH 0.3-1.05A 54V S 230V	3	110x74x32	0.3-1.05	24-54	*	*	*	8718696 683682 00
Xitanium 36W LH 0.3-1A 48V I 230V	2	190x46x32	0.3-1	24-48	*	*	*	8718696 542439 00
Xitanium 36W/m 0.3-1.05A 54V 230V	5	97x43x30	0.3-1.05	24-54	*	*	*	8718696 659052 00
Xitanium 36W/m 0.3-1.05A 48V 230V	5	97x43x30	0.3-1.05	24-48	*	*		8718291 750277 00
Xitanium 20W WH 0.15-0.5A 54V Is 230V	6	200x74x32	0.15-0.5	24-54	*	*	*	8718696 683606 00
Xitanium 20W WH 0.15-0.5A 54V S 230V	3	110x74x32	0.15-0.5	24-54	*	*	*	8718696 683668 00
Xitanium 20W LH 0.15-0.5A 48V Is 230V	1	150x46x32	0.15-0.5	24-48	*	*	*	8718696 474044 00
Xitanium 20W/m 0.15-0.5A 54V 230V	5	97x43x30	0.15-0.5	24-54	*	*	*	8718696 659038 00
Xitanium 20W/m 0.15-0.5A 48V 230V	5	97x43x30	0.15-0.5	24-48	*	*		8718291 766636 00